

Generator de curent trifazic cu benzina Stanley SG5600B 5500W

SPECIFICATII TEHNICE	SG5600B
Tip motor	un singur cilindru racit cu aer,4 timpi OHV
Capacitate cilindrica:	389 cm3
Tip combustibil	benzina normala fara plumb
Capacitate rezervor combustibil/ulei	25L / 1.1L
Putere maxima 400V	5.500 W
Putere maxima 230V	3.300 W
Putere nominala 400V	5.000 W
Putere nominala 230V	3.000 W
Sistem pornire	Pornire manuala /electrica
Numar prize	2x230V / 1x400V
Autonomie	9.15 h(cu rezervorul plin)
Consum mediu	0.3 L/ kwh consumat
Protectie la supracina/ nivel scazut de ulei	Da /Da
Tip generator	Sincron
Greutate	76 Kg
Nivel de zgomot garantat (LWA)	97 dB(A)
Functii	Manere si roti

