



PNI PT101L & PNI PT202L



Caracteristici de baza

- »Control vocal prin Amazon Alexa, Google Home.
- »Control de la distanta prin Tuya Smart (Android/iOS)
- »Programare stingere automata lumina prin Tuya Smart.
- »Buton tactil capacitiv sensibil cu LED (albastru-lumini stinse, rosu - lumini aprinse).
- »Panou frontal din sticla securizata rezistenta la zgariere.
- »Protectie la suprasarcina.
- »Nu necesita cablu de nul.

Specificatii tehnice

- »Curent nominal: 10A
- »Tensiune nominala: 230V
- »Frecventa: 2.4GHz WiFi
- »Puterea de transmisie: 100mW
- »Standard Wireless: IEEE 802.11b/g/n
- »Aplicatie compatibila: Tuya Smart/Smart Life